A Compact 2-D Full-Wave Finite-Difference Frequency-Domain Method for General Guided Wave Structures

Yong-Jiu Zhao, Ke-Li Wu, Senior Member, IEEE, and Kwok-Keung M. Cheng, Member, IEEE

Abstract—A compact two-dimensional (2-D) full-wave finite-difference frequency-domain method is proposed for the analysis of dispersion characteristics of a general guided wave structure. Because the longitudinal field components are eliminated in the proposed method, only four transverse field components are involved in the final resulting eigen equation. This feature considerably reduces the required CPU time as compared to the existing approaches by which six field components are comprised. Additionally, unlike other 2-D finite-difference schemes that determine the eigenfrequency for a given propagation constant, the new method finds the propagation constant β for a given k_0 (frequency). The new method has been verified by examining the computed results of a number of typical guided wave structures with the published results. Very good agreement is achieved.

Index Terms—Anisotropic media, eigenvalues and eigenfunctions, finite-difference methods, frequency-domain analysis, waveguide.

I. INTRODUCTION

► HE determination of the dispersion characteristics of a general guided wave structure is a very important subject in practical engineering designs. Numerous full-wave techniques tackling the problems have been proposed by many researchers [1]-[8]. For example, the approach used to determine the characteristics in [1] is based on a three-dimensional (3-D) finite-difference time-domain (FDTD) simulation. Because the method involves a 3-D mesh, large memory space and long CPU time are required. To alleviate these problems, Xiao et al. introduced a two-dimensional (2-D) FDTD approach that uses only a 2-D mesh consisting of all six field components [2]. In the approach, the propagation constant is given as an input parameter for solving for eigenfrequencies. A further step was taken to reduce the grid to a truly 2-D grid by approaching the mesh size in the propagation direction to zero [4]. To avoid dealing with complex variables and to improve the efficiency, a variable transformation was introduced that leads to a real-variable algorithm [5]. Hong and Park applied the real-variable 2-D compact

Y.-J. Zhao is with the Department of Electronics Engineering, The Chinese University of Hong Kong, Shatin, Hong Kong and also with the School of Mechano-Electronic Engineering, Xidian University, Xi'an, China.

K.-L. Wu and K.-K. M. Cheng are with the Department of Electronic Engineering, The Chinese University of Hong Kong, Shatin, Hong Kong (e-mail: klwu@ee.cuhk.edu.hk).

Publisher Item Identifier 10.1109/TMTT.2002.800447.

FDTD to the analysis of the dispersion characteristic of a unilateral fin-line in [6].

Although the above-mentioned 2-D FDTD approaches have the advantages of CPU time and memory saving over those 3-D methods, they all need to give the propagation constant β as an input parameter and have to find the eigenfrequencies of interest via discrete Fourier transform. To cope with the predicament, a novel 2-D finite-difference frequency-domain (FDFD) algorithm was proposed recently [7], in which the propagation constant is sought for a given frequency. However, all the six field components need to be employed to yield an eigen equation.

In this paper, a compact 2-D full-wave FDFD method is proposed for solving for propagation constant β of a general transmission line for a given k_0 (frequency). To convert a physical guided wave problem into an eigen problem, only four transverse field components are involved. The resultant eigen equation is constructed by a highly sparse matrix. In contrast to the existing approaches that use six field components, the new method is much more efficient in computation. Needless to say that the feature of finding β for a given k_0 is more pertinent in practical applications.

II. THEORY

It is assumed that the guided wave structure is uniform along axis z and the wave propagates in the positive z direction. The fields in a general guided wave structure can be expressed as

$$\overline{E}(x, y, z) = [E_x(x, y)\hat{x} + E_y(x, y)\hat{y} + E_z(x, y)\hat{z}]e^{-j\beta z}$$
(1)
$$\overline{H}(x, y, z) = [H_x(x, y)\hat{x} + H_y(x, y)\hat{y} + H_z(x, y)\hat{z}]e^{-j\beta z}$$
(2)

where the time variation of $e^{j\omega t}$ is suppressed. Therefore, the derivatives with respect to z can be replaced by $\partial/\partial z = -j\beta$.

Although the approach proposed is applicable to a general anisotropic type of transmission line, for the simplicity of illustration, the derivation below will be limited to the case of electric anisotropic media with diagonal dielectric constant tensor $\overline{\overline{e_r}}$. By normalizing field components with square root of the free-space wave impedance such that $\overline{H'} = \overline{H} \cdot \sqrt{\eta_0}$ and $\overline{E'} = \overline{E}/\sqrt{\eta_0}$, Maxwell's curl equations become

$$-jk_0\vec{H} = \nabla \times \vec{E} \quad jk_0\overline{\overline{c_r}} \cdot \vec{E} = \nabla \times \vec{H}$$
(3)

Manuscript received September 12, 2000; revised June 13, 2001. This work was supported by the Research Grants Council of the Hong Kong Special Administrative Region (2150237/4213/00E) under a grant.





Fig. 1. Conventional Yee's 3-D lattice.

where the prime sign is omitted for the sake of simplicity.

With Yee's grid system shown in Fig. 1, (3) can be discretized as

$$\begin{cases} H_x(i, j) = j \frac{1}{k_0 h_y} \left[E_z(i, j+1) - E_z(i, j) \right] \\ -\frac{\beta}{k_0} e^{-j\Delta} E_y(i, j) \\ H_y(i, j) = \frac{\beta}{k_0} e^{-j\Delta} E_x(i, j) \\ -j \frac{1}{k_0 h_x} \left[E_z(i+1, j) - E_z(i, j) \right] \\ H_z(i, j) = j \frac{1}{k_0 h_x} \left[E_y(i+1, j) - E_y(i, j) \right] \\ -j \frac{1}{k_0 h_y} \left[E_x(i, j+1) - E_x(i, j) \right] \end{cases}$$
(4)

and

$$\begin{cases} \varepsilon_{xx} E_x(i, j) = -j \frac{1}{k_0 h_y} [H_z(i, j) - H_z(i, j-1)] \\ + \frac{\beta}{k_0} e^{-j\Delta} H_y(i, j) \\ \varepsilon_{yy} E_y(i, j) = j \frac{1}{k_0 h_x} [H_z(i, j) - H_z(i-1, j)] \\ - \frac{\beta}{k_0} e^{-j\Delta} H_x(i, j) \\ \varepsilon_{zz} E_z(i, j) = -j \frac{1}{k_0 h_x} [H_y(i, j) - H_y(i-1, j)] \\ + j \frac{1}{k_0 h_y} [H_x(i, j) - H_x(i, j-1)] \end{cases}$$
(5)

where h_x , h_y and h_z are mesh sizes in x, y, and z directions, respectively, and $\Delta = \beta h_z/2$.

As h_z approaches zero, the Yee's grid is reduced to a compact 2-D grid as shown in Fig. 2. Consequently, (4) and (5) become the following 2-D form:



$$\begin{cases} H_x(i, j) = j \frac{1}{k_0 h_y} \left[E_z(i, j+1) - E_z(i, j) \right] - \frac{\beta}{k_0} E_y(i, j) \\ H_y(i, j) = \frac{\beta}{k_0} E_x(i, j) \\ -j \frac{1}{k_0 h_x} \left[E_z(i+1, j) - E_z(i, j) \right] \\ H_z(i, j) = j \frac{1}{k_0 h_x} \left[E_y(i+1, j) - E_y(i, j) \right] \\ -j \frac{1}{k_0 h_y} \left[E_x(i, j+1) - E_x(i, j) \right] \\ \text{and} \end{cases}$$
(6)

$$\begin{cases} \varepsilon_{xx} E_x(i, j) = -j \frac{1}{k_0 h_y} \left[H_z(i, j) - H_z(i, j-1) \right] \\ + \frac{\beta}{k_0} H_y(i, j) \\ \varepsilon_{yy} E_y(i, j) = j \frac{1}{k_0 h_x} \left[H_z(i, j) - H_z(i-1, j) \right] \\ - \frac{\beta}{k_0} H_x(i, j) \\ \varepsilon_{zz} E_z(i, j) = -j \frac{1}{k_0 h_x} \left[H_y(i, j) - H_y(i-1, j) \right] \\ + j \frac{1}{k_0 h_y} \left[H_x(i, j) - H_x(i, j-1) \right]. \end{cases}$$
(7)

Eliminating E_z and H_z from (6) and (7), we obtain

$$\begin{aligned} \frac{\beta}{k_0} E_x(i, j) \\ &= -\frac{1}{k_0^2 \varepsilon_{zz} h_x h_y} \left[H_x(i, j-1) - H_x(i+1, j-1) \right. \\ &- H_x(i, j) + H_x(i+1, j) \right] \\ &+ \frac{1}{k_0^2 \varepsilon_{zz} h_x^2} H_y(i-1, j) + \left(1 - \frac{2}{k_0^2 \varepsilon_{zz} h_x^2} \right) H_y(i, j) \\ &+ \frac{1}{k_0^2 \varepsilon_{zz} h_x^2} H_y(i+1, j) \end{aligned}$$
(8)

$$\frac{\beta}{k_0} E_y(i, j) = -\frac{1}{k_0^2 \varepsilon_{zz} h_y^2} H_x(i, j-1) - \left(1 - \frac{2}{k_0^2 \varepsilon_{zz} h_y^2}\right) H_x(i, j) \\
- \frac{1}{k_0^2 \varepsilon_{zz} h_y^2} H_x(i, j+1) + \frac{1}{k_0^2 \varepsilon_{zz} h_x h_y} \\
\cdot [H_y(i-1, j) - H_y(i, j) - H_y(i-1, j+1) + H_y(i, j+1)]$$
(9)

$$\frac{\beta}{k_0} H_x(i, j) = \frac{1}{k_0^2 h_x h_y} \left[E_x(i-1, j) - E_x(i, j) - E_x(i-1, j+1) + E_x(i, j+1) \right] - \frac{1}{k_0^2 h_x^2} E_y(i-1, j) - \left(\varepsilon_{yy} - \frac{2}{k_0^2 h_x^2} \right) E_y(i, j) - \frac{1}{k_0^2 h_x^2} H_y(i+1, j) \quad (10)$$

$$\frac{\beta}{1} H_y(i, j)$$

$$k_{0} = \frac{1}{k_{0}^{2}h_{y}^{2}} E_{x}(i, j-1) + \left(\varepsilon_{xx} - \frac{2}{k_{0}^{2}h_{y}^{2}}\right) E_{x}(i, j) + \frac{1}{k_{0}^{2}h_{y}^{2}} E_{x}(i, j+1) - \frac{1}{k_{0}^{2}h_{x}h_{y}} \cdot [E_{y}(i, j-1) - E_{y}(i+1, j-1) - E_{y}(i, j) + E_{y}(i+1, j)].$$
(11)

Because the longitudinal components have been eliminated in the final equations, the boundary condition $E_z = 0$ on the surface of conductors has to be reflected indirectly. It can be done by inserting the boundary condition into (6) and (7) and systematically modifying (8)–(11) accordingly. For example, for $E_z(i + 1, j) = 0$ in (6), (8) will take the form of

$$\frac{\beta}{k_0} E_x(i, j) = -\frac{1}{k_0^2 \varepsilon_{zz} h_x h_y} \left[H_x(i, j-1) - H_x(i, j) \right] \\
+ \frac{1}{k_0^2 \varepsilon_{zz} h_x^2} H_y(i-1, j) + \left(1 - \frac{1}{k_0^2 \varepsilon_{zz} h_x^2} \right) H_y(i, j).$$
(12)

As in FDTD, the continuity condition of electric fields across two dielectric mediums is ensured by setting the dielectric constant on the interface as the average of the dielectric constants in the two regions.

After implementing all the boundary conditions, (8)–(11) can be concluded as an eigen problem as

$$[A] \cdot \{x\} = \lambda\{x\} \tag{13}$$

where [A] is the right-hand sparse matrix coefficient listed in (8)–(11), $\lambda = \beta/k_0$, and $\{x\} = \{E_x, E_y, H_x, H_y\}^T$. The conductor boundary conditions for transverse electric field components can be applied straightforwardly. For the convenience of applying the boundary conditions for the transverse electric



Fig. 3. Typical guided wave structures. (a) Rectangular waveguide. (b) Boxed microstrip line with anisotropic substrate. (c) Unilateral fin-line. (d) Partially filled inhomogeneous dielectric loaded waveguide.

field components, (13) can be rewritten as a generalized eigenvalue problem

$$[A] \cdot \{x\} = \lambda[B] \cdot \{x\} \tag{14}$$

where [B] is a unit matrix. Since the eigenvalue λ of interest will not equal zero, the zero boundary condition of the *i*th element of vector $\{x\}$ can be implemented by multiplying a very large number, for example, 10^{20} to the matrix elements a_{ii} and b_{ii} such that the *i*th equation is dominated by $10^{20}(a_{ii} - \lambda b_{ii})x_i =$ 0 or $x_i = 0$.

III. NUMERICAL RESULTS

To verify the proposed method, several typical guided wave structures are analyzed. As the first example, an empty rectangular waveguide with width a = 19.05 mm and height b = 9.525 mm, as shown in Fig. 3(a), is analyzed for not only the fundamental mode but also the first four higher order modes. The calculated numerical results are compared with the exact solution. As shown in Fig. 4(a), good agreement is obtained. To validate the method for the cutoff modes, the first three modes in the rectangular waveguide are also calculated when they are under cutoff and the results are presented in Fig. 4(b) along with the exact solutions.

The second case is a boxed microstrip line with electric anisotropic substrate, as shown in Fig. 3(b). The width and the height of the metallic box are a = 6.5 mm and b = 3.5 mm, respectively. The dielectric diagonal constant tensor of the substrate is given by $\varepsilon_{xx} = \varepsilon_{zz} = 9.4$, and $\varepsilon_{yy} = 11.6$, and its thickness h = 1.5 mm. The width of the strip w = 1.5 mm and the thickness is negligible. The computed result is superposed with that calculated by FDTD in [4] in Fig. 5 with good correlation.

The third example is an unilateral fin-line with the geometry shown in Fig. 3(c), in which a = 20 mm, b = 10 mm, d = 1 mm, and s = 4 mm. The relative permittivity of the dielectric



Fig. 4. Dispersion characteristics of a rectangular waveguide. (a) Propagation constant. (b) Attenuation constant.



Fig. 5. Dispersion characteristics of a boxed microstrip line with anisotropic substrate.

slab is $\varepsilon_r = 2.22$. The result calculated by the proposed method and that obtained in [3] are superimposed in Fig. 6.

Finally, a partially inhomogeneous dielectric loaded waveguide as shown in Fig. 3(d) is analyzed. The dimensions of the structure are a = 10.16 mm, b = 5.588 mm, c = 3.048 mm, and d = 5.08 mm. The relative permittivity of the slab is $\varepsilon_r = 8$. The dispersion curves of the first two modes are obtained and



Fig. 6. Dispersion characteristics of a unilateral fin-line.



Fig. 7. Dispersion characteristics of a partially filled inhomogeneous dielectric loaded waveguide.

 TABLE I

 COMPARISON OF THIS METHOD AND SIX-COMPONENT METHOD

		This Method	The Six-component Method
Number of non- zero elements	waveguide	2412	1972
	microstrip	2520	2083
CPU time (sec.)	waveguide	6.04	16.76
	microstrip	15.65	59.49

are compared with that of Ansoft-HFSS. As shown in Fig. 7, excellent agreement can be observed.

It is worthwhile mentioning that the example of inhomogeneous dielectric loaded waveguide in [8] is also calculated with this method. For the sake of briefness, the result is not presented here. Excellent agreement has been obtained between the result of this method and that of biorthonormal-basis method, which falls in a totally different category of numerical method.

Although the elimination of longitudinal components does not help to reduce the memory requirement due to the number of terms in remaining equations increases, the CPU time is considerably reduced as compared to the case in which six field components are comprised. The comparison of efficiency in calculating dispersion curves of dominant mode in rectangular waveguide [Fig. 3(a)] and boxed microstrip line [Fig. 3(b)] is shown in Table I. The calculations are carried out on a Pentium III 800 computer using Matlab 6.0.

IV. CONCLUSION

In this paper, a novel compact 2-D full-wave FDFD method has been proposed for the analysis of the dispersion characteristics of a general guided wave structure. In the algorithm, only four transverse field components are employed in the final resulting eigen equation. Therefore, it is more efficient than the existing approaches involving six field components. Furthermore, since the algorithm determines β for a given k_0 (frequency), it is significantly more attractive and promising in practical applications than the existing methods that inversely seek k_0 for a given β . Additionally, it has been verified that this method also works very well for the modes under cutoff.

ACKNOWLEDGMENT

The authors would like to thank the reviewers for their valuable comments that have made the work in this paper more presentable.

REFERENCES

- D. H. Choi and W. J. R. Hoefer, "The finite-difference-time-domain method and its applications to eigenvalue problems," *IEEE Trans. Microwave Theory Tech.*, vol. MTT-34, pp. 1464–1470, Dec. 1986.
- [2] S. Xiao, R. Vahldieck, and H. Jin, "Full-wave analysis of guided wave structures using a novel 2_D FDTD," *IEEE Microwave Guided Wave Lett.*, vol. 2, pp. 165–167, May 1992.
- [3] F. Arndt, V. J. Brankovic, and D. V. Krupezevic, "An improved FD-TD full wave analysis of arbitrary guiding structures using a two-dimensional mesh," in *IEEE MTT-S Int. Microwave Symp. Dig.*, 1992, pp. 389–392.
- [4] A. Asi and L. Shafai, "Dispersion analysis of anisotropic inhomogeneous waveguides using compact 2D-FDTD," *Electron. Lett.*, vol. 28, pp. 1451–1452, July 1992.
- [5] S. Xiao and R. Vahldieck, "An efficient 2-D FDTD algorithm using real variables," *IEEE Microwave Guided Wave Lett.*, vol. 3, pp. 127–129, May 1993.
- [6] I. P. Hong and H. K. Park, "Dispersion characteristics of a unilateral fin-line using 2D FDTD," *Electron. Lett.*, vol. 32, pp. 1992–1994, Oct. 1996.
- [7] M.-L. Lui and Z. Chen, "A direct computation of propagation constant using compact 2-D full-wave eigen-based finite-difference frequencydomain technique," in *Proc. Int. Comput.l Electromagn. Its Applicat. Conf.*, Beijing, China, Nov. 1999, pp. 78–81.
- [8] E. Silvestre, M. A. Abian, B. Gimeno, A. Ferrando, M. V. Andres, and V. E. Boria, "Analysis of inhomogeneously filled waveguides using a bi-orthonormal-basis method," *IEEE Trans. Microwave Theory Tech.*, vol. 48, pp. 589–596, Apr. 2000.

Yong-Jiu Zhao was born in Hebei Province, China, in 1964. He received the M.Eng. and Ph.D. degrees in electronic engineering from Xidian University, Xi'an, China, in 1990 and 1998, respectively.

Since March 1990, he has been with the Department of Measurement and Controlling Engineering and Instruments, School of Mechano-Electronic Engineering, Xidian University. From Dec. 1999 to Aug. 2000, he was a Research Associate in the Department of Electronic Engineering, The Chinese University of Hong Kong. His current fields of

interest include computational electromagnetics and microwave components and subsystems.



Ke-Li Wu (M'90–SM'96) received the B.S. and M.Eng degrees from Nanjing University of Science and Technology, Nanjing, China, in 1982 and 1985, respectively, and the Ph.D. degree from Laval University, Quebec, QC, Canada, in 1989.

From 1989 to 1993, he was with the Communications Research Laboratory, McMaster University, Montreal, QC, Canada, as a Research Engineer and a Research Group Manager. In March 1993, he joined the Corporate R&D Division, Com Dev International, where he had been a Principle Member

of Technical Staff in charge of developing advanced electromagnetic design software for various microwave subsystems for communication satellites and wireless communications. Since October 1999, he has been with the Department of Electronic Engineering, The Chinese University of Hong Kong, Hong Kong, as an Associate Professor. He also holds an appointment as an Adjunct Associate Professor at McMaster University. He has authored or coauthored numerous publications in the areas of EM modeling and microwave and antenna engineering. He holds one Canadian patent and one U.S. patent. He contributed to *Finite Element and Finite Difference Methods in Electromagnetics Scattering* (Amsterdam, The Netherlands: Elsevier, 1990) and *Computational Electromagnetics* (Amsterdam, The Netherlands: Elsevier, 1991). His current research interests include all the aspects of numerical methods in electromagnetics, various passive microwave circuits, integrated antenna arrays, and LTCC multichip modules (MCMs) for wireless communications.

Dr. Wu was the recipient of a 1992 URSI Young Scientist Award. He was also the recipient of the 1993 Industry Feedback Award from the Telecommunication Research Institute of Ontario, Canada, and the 1998 Com Dev Achievement Award.



Kwok-Keung M. Cheng (S'90–M'91) received the B.Sc. degree (with first-class honors) in electrical engineering and the Ph.D. degree from King's College, University of London, London, U.K., in 1987 and 1993, respectively.

From 1990 to 1992, he was a Research Assistant at King's College, where he was involved in the area of hybrid circuit and MMIC design. From 1993 to 1995, he was a Post-Doctoral Research Associate, involved in the investigation of coplanar structures for microwave/millimeter-wave application. In 1996, he

became an Assistant Professor in the Department of Electronic Engineering, The Chinese University of Hong Kong, Hong Kong. He has authored or coauthored over 35 papers published in leading international journals and conferences, and was a contributing author of *MMIC Design* (London, U.K.: IEE Press, 1995). His current research interests are concerned with the design of MMICs, oscillators, active filters, and power amplifiers.

Dr. Cheng was the recipient of the 1986 Siemens Prize, the 1987 Institution of Electrical Engineers Prize, and the 1988 Convocation Sesquicentennial Prize in Engineering (University of London).